



Europäisches Patentamt  
European Patent Office  
Office européen des brevets



(11) **EP 0 686 985 B1**

(12) **EUROPEAN PATENT SPECIFICATION**

(45) Date of publication and mention  
of the grant of the patent:  
10.09.1997 Bulletin 1997/37

(51) Int Cl.<sup>6</sup>: **H01F 27/02, H01F 27/29,  
H04R 1/06, H04R 25/00**

(21) Application number: **95110964.4**

(22) Date of filing: **26.11.1990**

(54) **Coil assemblies**

Spulenordnungen

Montages de bobine

(84) Designated Contracting States:  
**AT BE CH DE DK ES FR GB GR IT LI LU NL SE**

(30) Priority: **21.12.1989 GB 8928899**

(43) Date of publication of application:  
**13.12.1995 Bulletin 1995/50**

(62) Document number(s) of the earlier application(s) in  
accordance with Art. 76 EPC:  
**90917231.4 / 0 505 382**

(73) Proprietor: **KNOWLES ELECTRONICS CO.**  
**Burgess Hill, West Sussex RH15 9LP (GB)**

(72) Inventors:

- **Salvage, Richard James**  
**Burgess Hill, West Sussex RH15 0NL (GB)**
- **Harrington, Steven John**  
**Steyning, West Sussex BN44 3NE (GB)**
- **Powell, Derek William**  
**Burgess Hill, West Sussex RH15 9HP (GB)**

(74) Representative:

**Dunlop, Brian Kenneth Charles et al**  
**c/o Wynne-Jones, Laine & James**  
**22 Rodney Road**  
**Cheltenham Gloucestershire GL50 1JJ (GB)**

(56) References cited:

**DE-A- 3 502 178**

**DE-A- 3 616 773**

Note: Within nine months from the publication of the mention of the grant of the European patent, any person may give notice to the European Patent Office of opposition to the European patent granted. Notice of opposition shall be filed in a written reasoned statement. It shall not be deemed to have been filed until the opposition fee has been paid. (Art. 99(1) European Patent Convention).

## Description

This invention relates to a hearing aid transducer and to a hearing aid including such a transducer.

In many applications, and particularly in the hearing aid industry, there is a need for very small electrical coils made of extremely fine wire. These coils have to be mounted into cases and the fine input and output wires have to be connected to terminals by significantly thicker wires. This results in many assembly problems, because the fine wire can only be manipulated under a microscope and is very liable to break and because, with current winding arrangements, there is no certainty where the leads of the coil may end up after winding. Another complication is that it is generally desirable to produce small coils without any internal former and this means that the coil is difficult to orientate and locate correctly in three-dimensions. (The only reference surfaces are the end faces and the tunnel).

DE-A-3616773 describes a hearing aid having an external case containing a flexible circuit which interconnects the electrical components of the aid and carries some of them. The circuit has terminals for the larger components such as the microphone. From one aspect the invention consists in a hearing aid transducer incorporating a case, a fine wire coil disposed within the case and having a set of leads and a flexible carrier incorporating electrical paths extending from a first set of terminals to a second set of terminals, the coil being mounted on the carrier and its leads being connected to the first set of terminals wherein the case has a slot through which the carrier extends such that its second set of terminals are external to the case.

In a preferred embodiment the carrier is flexible and may, for example, be constituted by a flexi-circuit. The connections between the leads of the first set of terminals are preferably formed by welding or some similar arrangement so as to avoid solder flux contamination.

Where the carrier is flexible it will be understood that the carrier can easily be bent to conform to the shape of the case and to pass around other elements of the device of which the coil assembly forms a part thus allowing a great range of configurations. Thus the carrier may extend above the coil or below the coil and its dimensions may be selected to locate particularly the coil within the case. The carrier may have a variety of second terminal configurations to suit the particular company using the devices and indeed the second terminals may be in the form of a plug-in connection.

The invention may be performed in various ways and specific embodiments will now be described, by way of example, with reference to the accompanying drawings, in which:

Figure 1 is a transducer assembly including a coil assembly according to the invention;

Figures 2 to 4 show alternative embodiments of such a transducer;

Figure 5 is a diagrammatic view from above of a winding machine for use in manufacture of the coil assemblies;

Figure 6 is an end view of the machine of Figure 5; and

Figures 7 and 8, 9 and 10 and 11 and 12 show view from above and one end in respective stages of the connection of a coil and its leads to a carrier.

In Figure 1 an acoustic transducer, generally indicated at 10, comprises a case 11, having a top 12 and a bottom 13, a diaphragm 14, a reed 15, a coil 16, mounted on a flexi-circuit carrier 17 and magnets/pole piece assembly 18.

As has been indicated above the coil 16 is formless so that it can be sufficiently small, whilst accommodating the reed 15, and it is carried on the flexi-circuit 17 by means of connections which will be described in more detail below. The flexible nature of the circuit enables the carrier to be curved downwardly around the coil and to extend out of the case 11, through a slot 19 and to be bent along the external face of the bottom 13 to present terminals 20 for connection to the rest of a device.

Figures 2 to 4 show alternative arrangements of the transducer 10 and they particularly well illustrate the dramatic effect of the use of a flexi-circuit in that it can be bent into various positions and can be formed to accommodate various configurations. This is particularly advantageous when it comes to manufacture, because a batch suitable for any particular use can be made simply by supplying the machine described below with the appropriate flex-circuits; no change is required in the manufacturing process. In contrast, with the present system, the assembly operatives have to select different pieces to achieve different constructions.

Turning to Figures 5 and 6 a winding machine 21 consists of a retractable coil former 22, a retractable tail stop 23, and a fly winder 24 which is retractably mounted on tail stop 23. The fly winder 24 is supplied from a spool 25. The machine 21 is arranged to operate with a series of pallets 26 which pass in this configuration from right to left. These pallets have leading and trailing retaining posts 27 and 28 which pick up the wire 29 as it passes from one coil to the next and retain it so that the posts define the positions of the start and trailing leads of the coil.

Thus in manufacturing a coil 16 is wound on the former 22 by the fly winder 24, having already had its start coil lead retained by the post 27 and once winding is complete the trailing lead becomes entrapped by the trailing post 28.

The pallet 26 would then normally be moved downstream to the next assembly stage, but for convenience a circuit positioning slide 30 is illustrated in winding location. As can be seen this slide holds the flexi-circuit 17 in position in a retracted position until the coil is wound. The slide is then brought forward to position the

circuit 17 under the coil 16. Alternatively, the circuit may be presented to the rod after it has been wound; the circuit being fed from a separate dispenser.

Referring now to Figure 7 to 12 it will be seen that once the circuit 17 is positioned beneath the coil 16 the leads 31 can be removed from their own positions defined by the posts 27 and 28 by robotic manipulating arms or the like and positioned on terminals 32 on the flexi-circuit 17. They are then preferably welded to the terminals 32 which leaves the coil 16 supported fractionally above the carrier 16. the coil is slid over and against the carrier 17 and the leads 31 brushed beside the coil. An adhesive is then placed between the edges of the coil 16 and the carrier 17. It will be seen that the terminals 32 are connected to terminals 20 by means of electrical paths 33.

As mentioned above it is more likely that the pallets 26 will be passed to a series of lead fixing and coil attaching stations after winding in order to achieve a greater throughput.

The resultant assembly enables the coil to be moved around within the assembly plant without the coil being touched, hence reducing the risk of damage, and they could even be supplied mounted on strips of flexi-circuits. Another advantage is that the connections between the coil and the terminal are protected by the flexi-circuit and the coil. The coil is located three-dimensionally by the flexi-circuit and the connections are formed without the need for thicker lead-out wires or other additional or complicated features as are currently used. The ability to achieve automatic assembly of the coil to its terminals considerably reduced the manufacturing costs and enables the assembly to be constructed in accordance with customer requirements very simply.

#### Claims

1. A Hearing aid transducer (10) incorporating a case (11), a fine wire coil (16) disposed within the case (11) and having a set of leads (31) and a flexible carrier (17) incorporating electrical paths extending from a first set of terminals (32) to a second set of terminals (20), the coil (16) being mounted on the carrier (17) and its leads being connected to the first set of terminals (32) wherein the case (11) has a slot (19) through which the carrier (17) extends such that its second set of terminals (20) are external to the case (11).
2. A transducer as claimed in Claim 1 wherein the coil is a formless coil.
3. A transducer as claimed in any one of the preceding claims, wherein the leads are welded to the first set of terminals.
4. A transducer as claimed in any one of the preceding

claims further comprising a plurality of coils mounted on the carrier.

5. A transducer as claimed in any one of the preceding claims wherein the second terminals lie along an external face of the case.
6. A transducer as claimed in any one of the preceding claims wherein the carrier extends above or below the coil.
7. A transducer as claimed in any one of the preceding claims wherein the carrier is dimensioned to locate the coil within the case.
8. A hearing aid including a transducer as claimed in any one of the preceding claims.

#### 20 Patentansprüche

1. Schallwandler (10) für Hörgeräte mit einem Gehäuse (11), einer Spule (16) aus dünnem Draht, die innerhalb des Gehäuses (11) angeordnet ist und mehrere Anschlußleitungen (31) aufweist, und einem flexiblen Träger (17), der elektrische Leiterbahnen aufweist, die sich von mehreren ersten Anschlußpunkten (32) zu mehreren zweiten Anschlußpunkten (20) erstrecken, wobei die Spule (16) auf dem Träger (17) befestigt ist und ihre Anschlußleitungen an die ersten Anschlußpunkte (32) angeschlossen sind und das Gehäuse (11) einen Schlitz (19) aufweist, durch den sich der Träger (17) erstreckt, so daß sich seine zweiten Anschlußpunkte (20) außerhalb des Gehäuses (11) befinden.
2. Schallwandler (10) nach Anspruch 1, dadurch gekennzeichnet, daß die Spule (16) als eine Spule ohne Wickelschablone ausgebildet ist.
3. Schallwandler (10) nach einem der vorangegangenen Ansprüche, dadurch gekennzeichnet, daß die Anschlußleitungen an die ersten Anschlußpunkte (32) geschweißt sind.
4. Schallwandler (10) nach einem der vorangegangenen Ansprüche, dadurch gekennzeichnet, daß er darüber hinaus eine Vielzahl von Spulen umfaßt, die auf dem Träger befestigt sind.
5. Schallwandler (10) nach einem der vorangegangenen Ansprüche, dadurch gekennzeichnet, daß die zweiten Anschlußpunkte (20) entlang einer äußeren Seitenfläche des Gehäuses verlaufen.
6. Schallwandler (10) nach einem der vorangegangenen Ansprüche, dadurch gekennzeichnet, daß der Träger (17) ober- oder unterhalb der Spule (16) ver-

läuft.

7. Schallwandler (10) nach einem der vorangegangenen Ansprüche, dadurch gekennzeichnet, daß der Träger (17) so bemessen ist; daß er die Spule (16) innerhalb des Gehäuses (11) positioniert. 5
8. Hörgerät mit einem Schallwandler (10) nach einem der vorangegangenen Ansprüche. 10

#### Revendications

1. Transducteur de prothèse auditive (10) comprenant un boîtier (11), une bobine de fil fin (16) disposée à l'intérieur du boîtier (11) et comportant une série de conducteurs (31) et un support souple (17) comprenant des chemins électriques qui s'étendent d'une première série de bornes (32) à une seconde série de bornes (20), la bobine (16) étant montée sur le support (17) et ses conducteurs étant reliés à la première série de bornes (32), étant précisé que le boîtier (11) possède une fente (19) à travers laquelle le support (17) s'étend de façon que sa seconde série de bornes (20) soit externe au boîtier (11). 15 20 25
2. Transducteur tel que défini dans la revendication 1, dans lequel la bobine est une bobine sans mandrin de bobinage. 30
3. Transducteur tel que défini dans l'une quelconque des revendications précédentes, dans lequel les conducteurs sont soudés à la première série de bornes. 35
4. Transducteur tel que défini dans l'une quelconque des revendications précédentes, comprenant en outre plusieurs bobines montées sur le support. 40
5. Transducteur tel que défini dans l'une quelconque des revendications précédentes, dans lequel les secondes bornes s'étendent le long d'une face externe du boîtier. 45
6. Transducteur tel que défini dans l'une quelconque des revendications précédentes, dans lequel le support s'étend au-dessus ou au-dessous de la bobine. 50
7. Transducteur tel que défini dans l'une quelconque des revendications précédentes, dans lequel le support est dimensionné pour loger la bobine à l'intérieur du boîtier. 55
8. Prothèse auditive comprenant un transducteur tel que défini dans l'une quelconque des revendications précédentes.





